



Worker Beware®

Electrical Safety Trainer's Guide

Contents

Introduction.....	2
Section One: Know Your Audience.....	2
Section Two: Electricity Basics.....	2
What Is Electricity?	2
The Electrical Distribution System.....	3
Section Three: Plan Your Session	3
Know Your Material.....	3
Make the Material Relevant.....	3
Tailor the Session to the Training Space, Audience Size and Allotted Time.....	3
Section Four: Your Five-Step Training for Survival.....	4
1) Advertise the Meeting.....	4
2) Pass a Sign-In Sheet	4
3) Offer an Overview.....	4
4) Present the <i>Worker Beware</i> Materials	4
5) Conduct a Discussion	4
Section Five: Electrical Safety Quiz	5

Introduction

The *Worker Beware* training program from Southern California Edison (SCE) is designed to provide contractors with the information they need to work safely around overhead and underground power lines.

This trainer's guide will help you make the most of the *Worker Beware* program. It contains five sections:

- **Know Your Audience.** An overview of contractors' learning preferences.
- **Electricity Basics.** Information on how electricity works and some terms to know.
- **Plan Your Session.** Tips for preparing an effective training session.
- **Your Five-Step Training for Survival.** Step-by-step training guidance.
- **Before and After Quiz.** Reproducible electrical safety quiz to help trainers and participants evaluate the program's impact.

Section One: Know Your Audience

Understanding how contractors learn best will help you tailor your training session to this unique audience. Take into consideration the following:

- **Contractors are very focused on working efficiently.** Contractors may face pressure to cut corners where safety is concerned in the interest of saving time and money. Acknowledging this from the start—and cautioning against it—will put you all “on the same page.”
- **Contractors tend to be action-oriented learners** who do best when given an opportunity to practice and repeat recommended behaviors.
- **Contractors prefer practical (rather than theoretical) information.** Keep the focus on real-life situations.

Section Two: Electricity Basics

This section will help you answer questions about electricity from session participants.

What Is Electricity?

Electricity results from the flow of electrons between atoms that occurs when atoms carry different charges. Electrons are negatively charged and flow to positively charged atoms until the charge is level or neutral.

- The flow of electrons is called **current**.
- Current is measured in **amperes**, or **amps** for short.
- The force propelling the flow of electrons is measured in **voltage**, or **volts** for short.
- When an object or substance limits the flow of current, this property is called **resistance**. Resistance is measured in **ohms**.
- Materials with a high level of resistance are called **insulators**. Common insulators include porcelain, plastics and air. These materials do not allow electricity to pass through them easily. (However, even insulators can conduct electricity under certain conditions.)

- Materials with a low level of resistance are called **conductors**. Common conductors include water, most metals and the human body. Electricity can pass easily through these materials under almost all conditions.

The Electrical Distribution System

Most of the nation's electricity is generated at power plants.

Wires on tall transmission towers carry high-voltage electricity from power plants to substations, where the voltage is typically reduced. From substations, electricity travels on wires that branch out down streets, either overhead or underground.

Overhead and underground power lines carry electricity to transformers on poles or in underground structures, where the voltage is reduced again to a level that is safe for use. From transformers, electricity travels into buildings through service wires. These wires connect to the meter panel, which is connected to all the wires that energize wall outlets and switches.

Note that Qualified Electrical Workers (QEW) receive extensive training and are experts in handling power lines. They also have special equipment for handling electric infrastructure. Contractors should understand that, even with training, their understanding of electricity is basic.

Section Three: Plan Your Session

A well-organized, informed instructor will gain participants' respect and be far more effective. Below are some recommendations to help you prepare for the electrical safety training session with confidence.

Know Your Material

Always preview the materials before showing them to session participants. Gathering information in advance can be useful and make the training materials more relevant. Review all the materials, and rehearse your presentation well before the session.

Make the Material Relevant

Identify the key situations that contractors in your training session may encounter, and focus the group's attention on these topics during training:

- **What job site situations** bring them close to overhead power lines?
- **What type of long or tall equipment do they use** that might come into contact with overhead power lines?
- **What type of digging activities** might bring them close to underground power lines?
- **What electrical hazards** have participants encountered in the past? Recently?

Tailor the Session to the Training Space, Audience Size, and Allotted Time

Remember that contractors are hands-on, action-oriented learners. The session will need to include opportunities to simulate recommended practices and to discuss potential applications of the material. Room size and arrangement can have a measurable impact on the participation level. Consider:

- **Will all materials be visible** to all participants, or do you need additional space or equipment?
- **Are the seats arranged in a way** that will foster discussion?
- **Is there adequate space** for participants to conduct simulations?
- **Is there adequate lighting** for all participants to see the instructor and materials, and to take notes if necessary?
- **Will everyone be able to hear?**

Just as room and audience size can impact the effectiveness of training, so can session time. No one learns well sitting for long periods. On the other hand, cramming too much information into a short session can reduce retention. Plan your session to allow time for discussions and simulations. If there is not enough time for all the materials, consider which ones will be most effective for participants.

Section Four: Your Five-Step Training for Survival

Follow these steps for a high-impact meeting that will keep participants involved and reinforce essential safety information:

1) Advertise the Meeting

Post a notice well in advance of the meeting in a highly visible location.

2) Pass a Sign-in Sheet

Keep attendance records of all safety meetings. Someday you may have to show who attended the meeting, what the session covered and when it was held.

3) Offer an Overview

Tell participants what you will cover in the meeting and what you hope they will learn. This is a good time to convey the importance of this information—that it can help protect contractors, their coworkers and the public from electrical-related injury or death.

4) Present the Worker Beware Materials

Discuss the electrical safety information in these materials and the electrical emergencies participants might encounter. Review these vital safety tips with participants periodically to refresh their memories.

5) Conduct a Discussion

Participants will retain more information if they get involved in a discussion. Here are some ideas:

- **Remind participants of the circumstances of any recent power line contacts** in your region. Discuss how information in the materials is relevant to those incidents.

- **Stress the requirement of contractors keeping themselves, their tools, their vehicles and their equipment (other than cranes and derricks used in construction) at least 10 feet* away from overhead power lines.**
**Occupational Safety & Health Administration (OSHA) requires at least 10 feet of clearance from power lines carrying 50 kV or less. Higher voltages require greater clearance distance. For safety clearance questions, call SCE at 1-800-611-1911.*
- **Keep cranes, derricks, manlifts and other tall equipment at least 20 feet away from power lines up to 350 kV.** Contact SCE and consult the Cal/OSHA regulations at dir.ca.gov/dosh for specific clearance requirements.
- **Review the proper 811 notification procedures and the utility color code.**
 Discuss why following the law and allowing extra time for a utility to mark underground lines can save time and money in the long run. Discuss additional safety measures, such as asking the property owner about underground lines.
- **Invite participants to ask questions** about the materials and the safety procedures they outline. If they have questions you can't answer, research the answers yourself and give them that information as soon as possible.
- **Ask participants to brainstorm a list of key safety issues** identified in the materials. Review these key issues, and discuss incidents that resulted when related safety precautions were ignored. What were the consequences?
- **Ask each participant to name one thing they learned** from the materials or discussion that will help them be safer in the future.

Remember that discussion is intended to reinforce proper behavior—not to call out or embarrass participants. Maintain a cooperative, supportive atmosphere at all times, and encourage participants to ask questions and provide feedback.

Section Five: Electrical Safety Quiz

The quiz on the next page is intended to help instructors and participants assess the program's effectiveness. Administer it before beginning the training, and ask participants to record their answers in the "Before" column. Then administer it again at the end of the session, and ask participants to list answers in the "After" column. The quiz is designed for two-sided photocopying.

Quiz Answers:

- | | |
|------|-------|
| 1. C | 6. A |
| 2. B | 7. B |
| 3. B | 8. A |
| 4. D | 9. D |
| 5. D | 10. B |

Name _____ Date _____

Worker Beware Electrical Safety Quiz

Before

Questions

After

- _____
1. For equipment other than cranes and derricks used in construction, what is the *minimum* safe clearance from overhead power lines?
- A. 6 inches
B. 100 feet
C. 10 feet
D. 5 feet
- _____
2. What is the color of the locator marks for underground electric power lines?
- A. Yellow
B. Red
C. Orange
D. None of the above
- _____
3. If you must work closer than the safe clearance distance from overhead power lines, which of the following should you do?
- A. Attempt to disconnect electrical service
B. Call SCE
C. Evacuate nearby homes
D. Both A and C
- _____
4. What does the law require that you do to determine the location of underground power lines before digging on a job site?
- A. Look for right-of-way markers
B. Check your maps
C. Call SCE
D. Notify DigAlert
- _____
5. How should you assist a coworker who contacts a power line while operating heavy equipment?
- A. Call 911, and inform the operator it is an electrical emergency
B. Encourage them to stay put until an SCE crew member arrives
C. If fire forces them off, tell them to jump clear without touching the equipment and the ground at the same time. They should land with their feet together, and then shuffle away with small steps
D. All of the above

_____ **6. True or false? Before digging, you should ask the property owner about any private underground lines that may not be marked by the locator.** _____

- A. True
- B. False

_____ **7. What is the job of a spotter?** _____

- A. To stabilize a load
- B. To prevent equipment from contacting power lines
- C. Both A and B
- D. None of the above

_____ **8. True or false? Your body can conduct electricity.** _____

- A. True
- B. False

_____ **9. If your equipment contacts a power line and you are not in imminent danger, you should:** _____

- A. Stay put and tell others to stay away and not to approach or touch the equipment
- B. Have someone immediately call 911 and SCE
- C. If there is danger from the fire or another hazard, jump clear of the equipment, keeping both feet together and without touching the ground and the equipment at the same time, and then shuffle away with small steps
- D. All of the above

_____ **10. True or false? You cannot be shocked by a service drop wire.** _____

- A. True
- B. False